

# Product datasheet

Specifications



High power contactor, TeSys Giga, 3 pole (3NO), AC-3 <=440V 800A, standard version, 100...250V wide band AC/DC coil

LC1G800KUEN

## Main

Range	TeSys
Range of product	TeSys Giga
Product or component type	Contactor
Device short name	LC1G
Contactor application	Power switching Motor control
Utilisation category	AC-1 AC-3 AC-3e AC-4 AC-5a AC-5b AC-6a AC-6b AC-8a AC-8b DC-1 DC-3 DC-5
Poles description	3P
[Ue] rated operational voltage	<= 1000 V AC 50/60 Hz <= 460 V DC
[Ie] rated operational current	1050 A (at <40 °C) at <= 1000 V AC-1 800 A (at <60 °C) at <= 440 V AC-3
[Uc] control circuit voltage	100...250 V AC 50/60 Hz 100...250 V DC
Control circuit voltage limits	Operational: 0.8 Uc Min...1.1 Uc Max (at <60 °C) Drop-out: 0.1 Uc Max...0.45 Uc Min (at <60 °C)

## Complementary

[Uimp] rated impulse withstand voltage	8 kV
Overvoltage category	III
[Ith] conventional free air thermal current	1050 A (at 40 °C)
Rated breaking capacity	5870 A at 440 V
[Icw] rated short-time withstand current	5.5 kA - 10 s 4.6 kA - 30 s 3.6 kA - 1 min 2.6 kA - 3 min 1.7 kA - 10 min
Associated fuse rating	800 A aM at <= 440 V for motor 630 A aM at <= 690 V for motor 1250 A gG at <= 690 V 1200 A UL Type L at <= 600 V

<b>Average impedance</b>	0.000065 Ohm
<b>[Ui] rated insulation voltage</b>	1000 V
<b>Power dissipation per pole</b>	70 W AC-1 - Ith 1050 A 42 W AC-3 - Ith 800 A
<b>Compatibility code</b>	LC1G
<b>Pole contact composition</b>	3 NO
<b>Auxiliary contact composition</b>	1 NO + 1 NC
<b>Motor power kW</b>	200 kW at 230 V AC 50/60 Hz (AC-3e) 335 kW at 400 V AC 50/60 Hz (AC-3e) 355 kW at 415 V AC 50/60 Hz (AC-3e) 375 kW at 440 V AC 50/60 Hz (AC-3e) 425 kW at 500 V AC 50/60 Hz (AC-3e) 560 kW at 690 V AC 50/60 Hz (AC-3e) 450 kW at 1000 V AC 50/60 Hz (AC-3e) 250 kW at 230 V AC 50/60 Hz (AC-3) 450 kW at 400 V AC 50/60 Hz (AC-3) 450 kW at 415 V AC 50/60 Hz (AC-3) 450 kW at 440 V AC 50/60 Hz (AC-3) 500 kW at 500 V AC 50/60 Hz (AC-3) 560 kW at 690 V AC 50/60 Hz (AC-3) 450 kW at 1000 V AC 50/60 Hz (AC-3) 200 kW at 230 V AC 50/60 Hz (AC-4) 375 kW at 400 V AC 50/60 Hz (AC-4) 355 kW at 415 V AC 50/60 Hz (AC-4) 375 kW at 440 V AC 50/60 Hz (AC-4) 400 kW at 500 V AC 50/60 Hz (AC-4) 475 kW at 690 V AC 50/60 Hz (AC-4) 400 kW at 1000 V AC 50/60 Hz (AC-4)
<b>Motor power hp</b>	300 hp at 200/208 V 60 Hz 350 hp at 230/240 V 60 Hz 700 hp at 460/480 V 60 Hz 800 hp at 575/600 V 60 Hz
<b>Irms rated making capacity</b>	7640 A at 440 V
<b>Coil technology</b>	Built-in bidirectional peak limiting
<b>Safety reliability level</b>	B10d = 100000 cycles contactor with nominal load conforming to EN/ISO 13849-1 B10d = 1800000 cycles contactor with mechanical load conforming to EN/ISO 13849-1
<b>Mechanical durability</b>	5 Mcycles
<b>inrush power in VA (50/60 Hz, AC)</b>	800 VA
<b>inrush power in W (DC)</b>	680 W
<b>hold-in power consumption in VA (50/60 Hz, AC)</b>	15.0 VA
<b>hold-in power consumption in W (DC)</b>	9.5 W
<b>Operating time</b>	40...70 ms closing 15...50 ms opening
<b>Maximum operating rate</b>	600 cyc/h AC-3 600 cyc/h AC-3e 300 cyc/h AC-1 150 cyc/h AC-4
<b>Connections - terminals</b>	Power circuit: bar 2 - busbar cross section: 52 x 20 mm Power circuit: lugs-ring terminals 1 185 mm <sup>2</sup> Power circuit: bolted connection Control circuit: push-in 1 0.2...2.5 mm <sup>2</sup> - cable stiffness: solid stranded without cable end Control circuit: push-in 1 0.25...2.5 mm <sup>2</sup> - cable stiffness: flexible with cable end Control circuit: push-in 2 0.5...1.0 mm <sup>2</sup> with cable end Control circuit: push-in 0.75...2.5 mm <sup>2</sup> - cable stiffness: solid stranded without cable end Control circuit: push-in 0.75...2.5 mm <sup>2</sup> - cable stiffness: flexible with cable end
<b>Connection pitch</b>	70 mm

<b>Mounting support</b>	Plate
<b>Standards</b>	EN/IEC 60947-4-1 EN/IEC 60947-5-1 UL 60947-4-1 CSA C22.2 No 60947-4-1 JIS C8201-4-1 JIS C8201-5-1 IEC 60335-1:Clause 30.2 IEC 60335-2-40:Annex JJ UL 60335-1 UL 60335-2-40:Annex JJ
<b>Product certifications</b>	CB Scheme CCC cULus EAC CE UKCA EU-RO-MR by DNV-GL
<b>Tightening torque</b>	58 N.m
<b>Height</b>	284 mm
<b>Width</b>	211 mm
<b>Depth</b>	266 mm
<b>Net weight</b>	14.2 kg

## Environment

<b>IP degree of protection</b>	IP2X front face with shrouds conforming to IEC 60529 IP2X front face with shrouds conforming to VDE 0106
<b>Ambient air temperature for operation</b>	-25...60 °C
<b>Ambient air temperature for storage</b>	-60...80 °C
<b>Mechanical robustness</b>	Vibrations 5...300 Hz 2 gn contactor open Vibrations 5...300 Hz 4 gn contactor closed Shocks 10 gn 11 ms contactor open Shocks 15 gn 11 ms contactor closed
<b>Colour</b>	Dark grey
<b>Protective treatment</b>	TH
<b>Permissible ambient air temperature around the device</b>	-40...70 °C at Uc

## Packing Units

<b>Unit Type of Package 1</b>	PCE
<b>Number of Units in Package 1</b>	1
<b>Package 1 Height</b>	30.000 cm
<b>Package 1 Width</b>	34.500 cm
<b>Package 1 Length</b>	60.500 cm
<b>Package 1 Weight</b>	16.416 kg
<b>Unit Type of Package 2</b>	S06
<b>Number of Units in Package 2</b>	2
<b>Package 2 Height</b>	75.000 cm
<b>Package 2 Width</b>	60.000 cm
<b>Package 2 Length</b>	80.000 cm
<b>Package 2 Weight</b>	42.832 kg



Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

### Environmental footprint

Total lifecycle Carbon footprint **2993**

Environmental Disclosure [Product Environmental Profile](#)

## Use Better

### Materials and Substances

Packaging made with recycled cardboard **Yes**

Packaging without single use plastic **No**

[EU RoHS Directive](#) **Compliant with Exemptions**

SCIP Number **6fbdad13-bb7c-47d4-a6d6-d82dd6f54349**

REACH Regulation [REACH Declaration](#)

Halogen-free status **Halogen free plastic parts product**

PVC free **No**

## Use Again

### Repack and remanufacture

Recyclability potential, in % **55**

End of life manual availability [End of Life Information](#)

Take-back **No**

WEEE Label  The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins

## Installation

### Installation Videos

---

[TeSys Giga - How to install the auxiliary contact block](#)

[TeSys Giga - How to install and remove remote wear diagnosis module](#)

[TeSys Giga - How to install mechanical interlock kit](#)

[TeSys Giga - How to install cable memory kit](#)

[TeSys Giga - How to directly mount LR9G overload relay](#)

[TeSys Giga - How to replace control module](#)

[TeSys Giga - How to replace switching modules](#)

[TeSys Giga - How to assemble reverser solution](#)

[TeSys Giga - How to assemble change-over solution](#)

## Technical Illustration

## Assembly's dimensions

