

# Product datasheet

Specifications



shunt trip SHT, EasyPact EZC100,  
EasyPact CVS100BS, 200 VAC to  
277 VAC 50/60 Hz

EZASHT200AC

## Main

Range	EasyPact GoPact
Range of product	EasyPact CVS EasyPact EZC GoPact R MCCB
Device short name	CVS100BS EZC100 GR12T
Product or component type	Voltage release
Device application	Control
Voltage release type	Shunt trip release
[Uc] control circuit voltage	200...277 V AC 50/60 Hz
Range compatibility	EasyPact EasyPact CVS CVS100BS GoPact R MCCB GR12T EasyPact EasyPact EZC EZC100

## Complementary

Operating threshold	0.7 Un tripping
Response time	50 ms
Auxiliary connection terminal	Lead wire

## Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	8.5 cm
Package 1 Width	7.0 cm
Package 1 Length	2.5 cm
Package 1 Weight	51.0 g

## Contractual warranty

Warranty	18 months
----------	-----------

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.



## Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

### Use Better

#### Materials and Substances

Packaging made with recycled cardboard	Yes
Packaging without single use plastic	Yes
<a href="#">EU RoHS Directive</a>	Compliant
REACH Regulation	<a href="#">REACH Declaration</a>

### Use Again

#### Repack and remanufacture

Take-back	No
WEEE Label	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins